

Marconi 7100

- **Country**
- [Great Britain \(UK\)](#)
- **Manufacturer / Brand**
- [Marconi Co. \(Marconiphone, Marconi's Wireless Telegraph Co. Ltd.\), GB \(not tubes - see also HMV His Master's Voice\)](#)
- **Year**
- 1948
- **Category**
- **Number of Tubes 6**
-
- **Valves / Tubes**

- Y61 X61M KTW61M U10 DH63 KT61
- **Main principle**
- Superheterodyne (common); ZF/IF 455 kHz
- **Wave bands**
- Broadcast, Long Wave and more than two Short Wave bands.
- **Power type and voltage**
- Alternating Current supply (AC) / 110; 125; 150; 205; 220; 245 Volt
- **Loudspeaker**
- Permanent Magnet Dynamic (PDyn) Loudspeaker (moving coil) / Ø 23 cm = 9.1 inch
- **Material**
- Wooden case
- **from Radiomuseum.org**
- Model: **7100** - Marconi Co. Marconiphone,
- **Shape**
- Tablemodel, low profile (big size).
- **Dimensions (WHD)**
- 490 x 350 x 260 mm / 19.3 x 13.8 x 10.2 inch
- **Notes**
- SW bands: 13m, 16m, 19m, 25m, 31m.
- **Net weight (2.2 lb = 1 kg)**
- 12.6 kg / 27 lb 12.1 oz (27.753 lb)

